

IP Hardware Firmware Upgrade Guide

RG-IP-RP1000-IP-HARDWARE-FIRMWAREQ216V1




Attention

1 Before asking for your IP Hardware firmware, please complete the following:


- Prepare the appropriate IP Hardware firmware. Otherwise, the data communication between the IP Hardware & PDU will fail after upgrade.
- Connect the IP Hardware to the computer either directly or remotely.

HOW TO UPGRADE THE IP HARDWARE FIRMWARE




- Step 1: Enter configured IP hardware address into the I.E. address bar**
- Enter the Login name & Password and click “Login” in the WEBUI login page


! Open the Internet Explorer (I.E.) version 9.0 or above



- Step 2: Select “Firmware” from the left navigation pane**



- Step 3: Click “Browse”**



- Step 4: Select the firmware file from the file location in the pop up window and click “Open”**

HOW TO REPLACE THE RP METER

Firmware

5 information

Device name: RackPower
Device IP address: 192.168.1.40
Device MAC address: 5A:48:54:3D:8E:3D
Firmware version: V2395S
Hardware revision: 2.0


Upgrade firmware

File path:

Warning Upgrading firmware may take a few minutes, please don't turn off the power or press the reset button.

Step 5: Click "Upgrade" to start the upgrade process


- It takes around 10 minutes to complete. Once complete, the login page will appear again.



Step 6a: If you are using RPM-04:


- » Click "Restart connection" to connect the upgraded IP hardware again

- END for Step 6a



Step 6b: If you are NOT using RPM-04:

- » Login the IP Hardware Web UI and select SNMP from the left navigation pane



- » Select Status from the left navigation pane & click "Search" to search the connected PDU(s)

- END for Step 6b



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN RAYCHEM SCHROFF TRACER

©2018 nVent. All nVent marks and logos are owned or licensed by nVent Services GmbH or its affiliates. All other trademarks are the property of their respective owners. nVent reserves the right to change specifications without notice.

H84284_1809

[nVent.com/SCHROFF](https://www.nvent.com/SCHROFF)